

Revised August 2025

The meter compartment of the meter base must be at least 11 inches wide

Center of Base
42 Inches Above Ground

Ring-type meter bases will not be accepted

MAIN DISCONNECT SWITCH

2" Rigid Metal or Sch 80 U.L.
Approved PVC Conduit

#4 Copper Ground Wire

Conduit Straps 2' Apart

5/8" X 8' Ground Rod
Driven Flush with or
Below Ground Level

6" X 6" Treated Post

Minimum 24" of cover over the top of conduit

Source

4-Wires to
Mobile Home

Pole Depth Approx. 3 Feet

Please contact North Arkansas Electric
Cooperative's engineering department
at 870-895-6213 before beginning work.

	Revisions		North Arkansas Electric Cooperative, Inc.				
			Salem, Arkansas		Arkansas-26-Fulton		
			200 Amp Service PEDESTAL - METER BASE DISCONNECT COMBINED				
			Date	Chk'd By	Drawn By	Scale	Dwg. No.
#	Description	Date	053100		RE		MPED2